

METRAport | 40S

Digital Multimeter

3-349-410-03
9/10.22

- Precision multimeter (V, A, Ω , F, Hz, %, °C/°F), Resolution: 10 μ V, 10 nA, 10 m Ω 4 $\frac{1}{4}$ -place
- TRMS measurement for V AC and I AC to 10 kHz
- DC measurement of 10 nA to 10 A via a single socket and a resettable fuse (**auto-fuse**), overload and blown fuse indicators
- Current measurement with current clamp sensors: The transformation ratio is adjustable from 1 mV:1 mA to 1 mV:1 A, and is accounted for by the display.
- Temperature measurement with automatic Pt sensor recognition
- Temperature measurement with type K thermocouple
- Capacitance and diode measurement
- Frequency measurement via V AC or I AC to 10 kHz
- Frequency and duty cycle measurement at 2 to 5 V signals up to 1 MHz
- RPM Measurement with Inductive Sensor (accessory)
- Automatic and manual measuring range selection
- Large backlit digital display with additional analog scale
- Measured value storage and min./max. recording
- **DAkKS certificate and 3 year guarantee**



Applications

The **METRAport 40S** digital multimeter is very well suited for universal use in general electrical engineering, electronics applications and for automotive service. Ideal reading angle adjustment is made possible by the tilt stand, and when suspended from the neck strap both hands are free for performing measurements. The instrument is switched off automatically when folded closed, and the display and the control panel are protected against damage.

Features

RMS Value with Distorted Waveshape

The utilized measuring method allows for waveshape independent TRMS AC measurement for voltage and current at up to 10 kHz.

Automatic / Manual Measuring Range Selection

Measured quantities are selected with the rotary switch. The measuring range is automatically matched to the measured values. The measuring range can be selected manually as well with the help of the AUTO/MAN key. Direct current measurement in all ranges via a single socket: measurement cable does not have to be replugged. Current clamp measurement is performed via a separate socket.

Automatic Storage of Measured Values

The DATA function allows for storage of the digitally displayed measured value. A special process assures that random values are not saved to memory in the case of rapidly changing measured quantities, but rather the actual measured value. The stored measured value appears at the digital display. The analog display continues to read out the current measured value.

Storage of Min-Max Values

In addition to displaying the current measured value, the minimum or maximum value can be continuously refreshed and saved to memory.

Continuity and Diode Testing, $I_k = 1 \text{ mA}$

This function can be used to test the polarity of diodes, and to test electrical circuits for short-circuits and interruptions. The test voltage source makes it possible to measure LEDs and reference diodes with up to 5.1 V. In addition to the display, an acoustic signal is generated during continuity testing of resistors within a range of 0 to 2 Ω .

Duty Cycle Measurement – Measurement of 5 V Square-Wave Signals

This function makes it possible to test circuits and transmission cables by measuring the frequency and the duty cycle of pulses with amplitudes of 2 to 5 V and frequencies of 100 Hz to 10 kHz.

Battery Charging Status – Power Saving Circuit

The battery charging status is indicated by means of a symbol with four different levels. The device is switched off automatically if the measured value remains unchanged for a period of 10 minutes, and if none of the controls are activated during this time. Automatic shutdown can be deactivated by switching the instrument to continuous operation.

Auto-Fuse and Fuse Detection for all Current Ranges

User-friendly thanks to resettable auto-fuses. Fuse detection: The FUSE message is displayed in order to indicate that the auto-fuse has blown. The fuse interrupts the current measuring ranges only. All other ranges remain functional.

METRAport | 40S

Digital Multimeter

Technical Data

Meas. Function	Measuring Range	Resolution with Upper Range Limit		Input Impedance	
		30 000	3 000	≡	~
μV DC	30 mV		10 μV	50 kΩ	—
V	300 mV	10 μV		> 11 MΩ	11 MΩ // < 50 pF
	3 V	100 μV		11 MΩ	11 MΩ // < 50 pF
	30 V	1 mV		10 MΩ	10 MΩ // < 50 pF
	300 V	10 mV		10 MΩ	10 MΩ // < 50 pF
				Approx. voltage drop at MRU	
A	300 μA	10 nA		160 mV	
	3 mA	100 nA		160 mV	
	30 mA	1 μA		180 mV	
	300 mA	10 μA		250 mV	
	3 A	100 μA		360 mV	
	10 A	1 mA		920 mV	
				Open-circuit voltage	Meas. current at MRU
Ω	30 Ω		10 mΩ	1.3 V	max. 250 μA
	300 Ω	10 mΩ		1.3 V	max. 250 μA
	3 kΩ	100 mΩ		1.3 V	max. 150 μA
	30 kΩ	1 Ω		1.3 V	max. 30 μA
	300 kΩ	10 Ω		1.3 V	max. 3 μA
	3 MΩ	100 Ω		1.3 V	max. 0.36 μA
	30 MΩ	1 kΩ		1.3 V	max. 0.1 μA
	⚡) 300 Ω	0.1 Ω ³⁾		max. 8.4V	Ik = 1 mA
➔) 5.1 V ¹⁾	1 mV		max. 8.4V	Ik = 1 mA	
			Discharge resistance	U _{0 max}	
F	30 nF		10 pF	10 MΩ	0.7 V
	300 nF		100 pF	1 MΩ	0.7 V
	3 μF		1 nF	100 kΩ	0.7 V
	30 μF		10 nF	11 kΩ	0.7 V
	300 μF		100 nF	3 kΩ	0.7 V
				f _{min} ²⁾	Power limit
Hz⁴⁾	300.0 Hz	0.01 Hz		1 Hz	3 x 10 ⁶ V x Hz
	3.0000 kHz	0.1 Hz		1 Hz	
	30.000 kHz	1 Hz		1 Hz	
	300.0 kHz	10 Hz		1 Hz	
	1000.0 kHz	100 Hz		1 Hz	
%	15...300 Hz: 2.0... 98.0%	0.1 %			3 x 10 ⁶ V x Hz
	... 3 kHz: 5.0... 95.0%	0.1 %			
	... 10 kHz: 10.0... 90.0%	0.1 %			
Upm1	60 ... 30 000	1			
Upm2	60 ... 30 000	2			
°C/°F	-200.0 ... +850.0 °C	Pt100	0.1 °C		
	-150.0 ... +850.0 °C	Pt1000	0.1 °C		
	-250.0 ... +1372.0 °C	K NiCr-Ni	0.1 °C		

- ¹ up to max. 5.1 V diode voltage, above which overload display appears: "OL".
² Lowest measurable frequency for sinusoidal measuring signals symmetrical to the zero point
³ Resolution with an upper range limit of 3000
⁴ Input sensitivity, signal/sine: Hz (V): 10 to 100% MR except for mV: as of 30% MR; Hz(f): 20 to 100% MR except for 3 A: as of 30% MR; Hz(clip): as of 30% MR

Key: d = digit(s), rdg. = reading (measured value), MR = measuring range
 MRU = upper range limit

Applicable Regulations and Standards

EN 61010-1	Safety requirements for electrical equipment for measurement, control and laboratory use – General requirements
EN 61326-1	Electrical equipment for measurement, control and laboratory use – EMC requirements – Part 1: General requirements
EN 60529	Test instruments and test procedures – degrees of protection provided by enclosures (IP code)

Meas. Range	Intrinsic Uncertainty for Max. Resolution under Reference Conditions		Overload Capacity ¹⁾	
	±(1... % rdg.l + ... d) ≡ ⁶⁾	±(1... % rdg.l + ... d) ~ ²⁾⁶⁾	Value	Time
30 mV	1 + 5	1 + 5	300 V ≡ (DC) ~ (AC) TRMS, sine	Continuous
300 mV	0.2 + 5 ⁴⁾	1 + 30		
3 V	0.2 + 3	0.5 + 30		
30 V	0.2 + 3	0.5 + 30		
300 V	0.2 + 3	0.5 + 30		
	≡ ⁶⁾	~ ²⁾⁶⁾		
300 μA	0.5 + 5	1.5 + 30	0.36 A	Continuous
3 mA	0.5 + 5	1.5 + 30		
30 mA	0.5 + 5	1.5 + 30		
300 mA	0.5 + 5	1.5 + 30		
3 A	0.7 + 5	1.5 + 30		
10 A	0.7 + 5	1.5 + 30		
			300 V ≡ (DC) ~ (AC) RMS sine	max. 10 s
30 Ω	1 + 5			
300 Ω	0.2 + 5 ⁴⁾			
3 kΩ	0.2 + 5 ⁴⁾⁷⁾			
30 kΩ	0.2 + 5			
300 kΩ	0.2 + 5			
3 MΩ	0.2 + 5			
30 MΩ	2 + 10			
⚡) 300 Ω	3 + 5			
➔) 5.1 V	0.5 + 3			
			300 V ≡ (DC) ~ (AC) RMS Sine	max. 10 s
30 nF	1 + 6 ⁴⁾			
300 nF	1 + 6			
3 μF	1 + 6			
30 μF	1 + 6			
300 μF	5 + 6			
		Max. measuring voltage		
300.0 Hz	0.1 + 5 ⁶⁾ (sinusoidal input voltage > 2 ... 5 V)	300 V	300 V	max. 10 s
3 kHz		300 V		
30 kHz		300 V		
300 kHz		100 V		
1000 kHz		10 V		
%	0.1 % rdg. ± 8 d		300 V	max. 10 s
	0.1 % rdg./kHz ± 8 d			
	0.1 % rdg./kHz ± 8 d			
		±Upm		
Upm1	60 ... 30 000	2	300 V	Continuous
Upm2	60 ... 30 000	2		
	Measuring Range	±(1... % rdg.l + ... d)		
Pt 100	-200.0 ... +850.0 °C	0.5% + 15 ⁵⁾	300 V ≡ (DC) / ~ (AC) TRMS, sine	max. 10 s
Pt 1000	-150.0 ... +850.0 °C	0.5% + 15 ⁵⁾		
K				
NiCr-Ni	-250.0 ... +1372.0 °C	1% + 5 K ⁵⁾		

- ¹ at 0 ° ... + 40 °C
² Values of less than 2 mV are suppressed in the 300 mV range, V_{AC} (A_{AC}) 15 ... 45 ... 65 Hz ... 10 (1) kHz sinusoidal.
³ Influencing factors see operating instructions.
⁴ After measurement with 10 A: at least 10 minute cool-down period
⁵ ZERO is displayed for "zero balancing" function.
⁶ plus sensor deviation
⁷ Specified intrinsic uncertainty is valid for 3 to 100 % of the AC measuring ranges. With short-circuited test probes:
 Residual value of 1 to 30 d at zero point due to TRMS converter to 1 kΩ: ±(0.2 + 9 D)
⁸

Reference Conditions

Ambient temperature	+23 °C ± 3 K
Relative humidity	40 ... 75 %
Measured qty. frequency	45 ... 65 Hz
Measured qty. waveshape	sine
Battery voltage	3 V ± 0.1 V

Display

LCD panel (95 × 40 mm) with analog and digital display including unit of measure, type of current and various special functions

Type COG (chip on glass) for good legibility from various directions

Background illumination

Background illumination (by means of LEDs) is activated with two keys, and is switched off automatically after approximately 1 minute.

Analog

Display LCD scale with pointer
 Scale length 80 mm for V $\overline{\text{---}}$ and A $\overline{\text{---}}$,
 67 mm for all other ranges
 Scaling \mp 5 ... 0 ... \pm 30 with 35 scale divisions for $\overline{\text{---}}$,
 0 ... 30 with 30 scale divisions in all other ranges

Polarity display With automatic switching
 Overflow display With triangle
 Measuring rate 20 measurements per second

Digital

Display / char. height 7-segment characters / 20 mm
 Number of places 4 $\frac{3}{4}$ places \cong 31000 steps
 Overflow display "OL" appears
 Polarity display "-" (minus sign) is displayed if plus pole is connected to "⊥"
 Measuring rate 2 measurements per second

Refresh rate

V $\overline{\text{---}}$ (DC), V~ (AC), A, Ω , \rightarrow ,
 °C (Pt100, Pt1000) 2 per second
 Hz 1 per second
 °C (K) 0.5 per second

Power Supply

Battery 2 ea. 1.5 V mignon cell, alkaline manganese per IEC LR6, zinc-carbon per IEC R6
 Service life With alkaline manganese: approx. 200 h
 With zinc-carbon: approx. 80 h
 Battery test Battery capacity display with battery symbol in 4 segments: "▣▣▣▣"
 Power saving circuit The device is switched off automatically:
 – If the measured value remains unchanged for a period of approximately 10 minutes, and if none of the controls are activated during this time. Automatic shutdown can be deactivated.
 – If battery voltage drops to below approx. 2.0 V

Fuses

Range 300 μ A to 10 A
 – Resettable auto-fuse 15 A, 240 V AC, 50 V DC
 – A slow-blow fuse is additionally connected in series to the auto-fuse, the blowing or absence of which is detected automatically (display "FUSE"); T16A/500V AC, 6.3 mm × 32 mm 1.5 kA switching capacity at 500 V AC and ohmic load

Electrical Safety

Safety class II per DIN EN 61140/VDE 0140-1
 Measuring category CAT II
 Operating voltage 300 V
 Fouling factor 2
 Test voltage 2.3 kV~ per EN 61010-1

Electromagnetic Compatibility (EMC)

Interference emission EN 61326-1 class B
 Interference immunity EN 61326-1
 EN 61326-2-1

Ambient Conditions

Accuracy range 0 °C ... +40 °C
 Operating temp. range –10 °C ... +50 °C
 Storage temp. range –25 °C ... +70 °C (without batteries)
 Relative humidity Max. 75%, no condensation allowed
 Elevation To 2000 m
 Deployment Indoors, except within specified ambient conditions

USB Interface

The USB port is electrically isolated from the measuring circuit.
 Operating voltage 5 V DC \pm 10% from USB Port of PC
 Current consumption 50 mA max, 25 mA typ.
 USB-Interface Type Mini-B, 5-pin, USB 1.1
 Transfer 38400 Baud
 parameters (1 Stopbit, no parity)
 Pinning 1: VCC, 2: D–, 3: D+, 4: ID/not assigned, 5: GND

METRAport | 40S

Digital Multimeter

Mechanical Design

Protection Housing: IP40, connector jacks: IP20
Table Excerpt Regarding Significance of IP Codes

IP XY (1 st char. X)	Protection against penetration of solid particles	IP XY (2 nd char. Y)	Protection against penetration by water
2	≥ 12.5 mm dia.	0	Not protected
4	≥ 1.0 mm dia.	0	Not protected

Dimensions 146 × 118 × 44 mm
Weight Approx. 450 g with batteries

Scope of Delivery

- 1 4½-place multimeter
- 2 1.5 V batteries
- 1 KS17-2 safety cable set
- 1 Carrying strap
- 1 Abbreviated operating instructions*
- 1 DAkkS certificate

* Detailed operating instructions are available for download on the Internet in the languages D, GB, F, E, S, I, DK, CZ, PL, P, TR at www.gossenmetrawatt.com

DAkkS Calibration Certificate

The multimeters are furnished with an internationally valid DAkkS calibration certificate (recognized by EA and ILAC). After the specified calibration interval has elapsed (recommended interval: 1 to 3 years), the multimeters can be recalibrated in our own DAkkS calibration laboratory.

Accessories flexible AC current sensor METRAFLEX 3000



Order Information

Description	Type	Article Number
4½-place digital multimeter with USB interface (connection Mini-B)	METRAport40S	M234D
Flexible AC current sensor 30/300/3000 A, 100 mV/10 mV/1 mV/A, 1%, Frequency range 10 Hz ... 20 kHz, with batteries, probe length 61 cm	METRAFLEX 3000 D)	Z207E
Current clamp sensor, 10 mA ... 100 A, 0.1 mV/mA	WZ12B D)	Z219B
AC current clamp sensor; measuring ranges 0.001 ... 15 AAC / 1 ... 150 AAC, transformation 1 V/A & 1 mV/A; frequency range 45 ... 500 Hz (-3 dB); clamp opening 15 mm dia.	WZ12C	Z219C
AC-/DC current clamp sensor, measuring ranges 30 A & 300 A, transformation 1 mV/A & 10 mV/A, resolution 50 mA & 100 mA; DC frequency range up to 20 kHz (-3 dB), clamp opening 25 mm dia.	CP330	Z202B
AC-/DC current clamp sensor, measuring ranges 180 A & 1800 A, transformation 10 mV/A & 1 mV/A, resolution 100 mA & 500 mA; DC frequency range up to 20 kHz (-1 dB), clamp opening 32 mm dia.	CP1800	Z204A
Pt100 temperature sensor for surface and emersion measurements, -40 to +600 °C	Z3409	GTZ3409000R0001
Dip-stick oil temperature sensor, Pt1000 class B, -50 to +500 °C, sensor: 3 mm dia. × 810 mm long	TF400CAR	Z102C
Quick-response surface temperature sensor (T90 = 2 s) thermocouple K (NiCr-Ni), -50 ... + 400 °C	TF400 SURFACE	Z102E

D) Data sheet available

Accessories current clamp sensors

WZ12B and WZ12C




CP330



© Gossen Metrawatt GmbH

Prepared in Germany • Subject to change without notice / Errors excepted • A PDF version is available on the Internet

All trademarks, registered trademarks, logos, product names, and company names are the property of their respective owners.

 **GOSSEN METRAWATT**
Gossen Metrawatt GmbH
Südwestpark 15
90449 Nürnberg • Germany

Phone +49 911 8602-0
Fax +49 911 8602-669
E-Mail info@gossenmetrawatt.com
www.gossenmetrawatt.com